



Author: PA3AKE		9MHz IF Notch	
TITLE: notch			
Document Number:			REU: B
Date: 9-3-2011 14:47:56			Sheet: 1/1

## Notch Board Rev-B Partlist

Part	Value	Package	Description
-Inductors-----			
L1	7.38uH	T80-6	(Micrometals T80-6, 40 turns, 0.6mm enameled copper)
L2	7.38uH	T80-6	(Micrometals T80-6, 40 turns, 0.6mm enameled copper)
L3	210nH	-	(Air coil, 5 turns, 0.8mm enameled, 10mm diameter, 8mm long)
-Capacitors-----			
C1	1p-7p	7.5mm, 3-pin	(Philips film trimmer, brown yellow)
C2	1p-7p	7.5mm, 3-pin	(Philips film trimmer, brown yellow)
C3	10p-120p	10mm, 3-pin	(Philips film trimmer, red)
C4	39p	-	(Polystyrene 2.5%)
C5	39p	-	(Polystyrene 2.5%)
C6	1n2	-	(Polystyrene 2.5%)
C7	180p	-	(Polystyrene 2.5%)
C4A	39p	1212	(American Technical Ceramics ATC100-B)
C5A	39p	1212	(American Technical Ceramics ATC100-B)
C6A	180p	1212	(American Technical Ceramics ATC100-B)
C7A	1n2	1212	(American Technical Ceramics ATC100-B)
-Connectors-----			
JP1	68020-172HLF	2x05	(10pins from FCI, Bergstik Header 72pin Right Angle)
JP2	68020-172HLF	2x05	(10pins from FCI, Bergstik Header 72pin Right Angle)

## Note:

Either Polysterene capacitors or ATC100-B chip capacitors can be used.

IF-NOTCH Rev-B

PA3AKE 08/03/2011





