

High power, High sensitivity 5 GHz Wifi Card SR5

Hi-performance 5GHz 802.1 a mini-PCI module

Designed for outdoor wireless applications

Super range radio technology

With improved output power

Ideal for long range

Compatibility with many platforms

High power up to 400 mW @ 24 Mbits/s

Better sensitivity over standard wireless cards

MMCX and UFL connector for extra compatibility



Specification

Power Consumption (Extreme)


Transmit 4.7W, +/- 300mW Receive 1.2W, +/- 200mW


Temperature Rating

Storage -70 - +85 C Operation -40 - +60C

Transmit Power

6-24 Mbps	26 dBm, +/- 1dB
36 Mbps	24 dBm, +/- 1dB
48 Mbps	22 dBm, +/- 1dB
54 Mbps	21 dBm, +/- 1dB





Receive Sensitivity

Rate	Level
6 Mbps	-94 dBm, +/- 2dB
9 Mbps	-93 dBm, +/- 2dB
12 Mbps	-91 dBm, +/- 2dB
18 Mbps	-90 dBm, +/- 2dB
24 Mbps	-86 dBm, +/- 2dB
36 Mbps	-83 dBm, +/- 2dB
48 Mbps	-77 dBm, +/- 2dB
54 Mbps	-74 dBm, +/- 2dB

The SR5 card will work seamlessly with any system and software that currently supports Atheros AR5004 mini-PCI cards. Maximum output power will appear as default irrespective of what the driver reports. Compatibility with many platforms has been verified including:











